

# MI-DCZRM Addressable Zone Monitor Module Data Sheet

## Product Overview

The MI-DCZRM addressable zone monitor module allows a zone of non-addressable devices to communicate with a Morley-IAS protocol analogue addressable system. As a result existing non-addressable zones can be integrated into a Morley-IAS protocol system.

The module monitors a zone of two-wire non-addressable devices. Each MI-DCZRM uses one of 99 available module addresses on a loop. A fault signal will be transmitted to the panel in case of an open circuit or short circuit on the non-addressable zone wiring or when the external fault input is pulled low (can be used for power supply monitoring). A flashing LED indicates that the module is in communication with the control panel. The LED latches steady on alarm (subject to current limitations).

The non-addressable zone can be powered from the analogue communication loop or from an external power supply. Where the non-addressable zone is powered from an external power supply, the communication loop is fully isolated from the non-addressable zone and from the power supply.

The zone monitor module replaces the MI-CZME but can be mounted onto a DIN rail. It can also be powered from the addressable loop and allows integration of non-addressable zones into an addressable system. This module enables non-addressable devices to be monitored by Morley-IAS protocol analogue addressable fire alarm control panels.

The maximum recommended number of non-addressable devices that can be used with the MI-DCZRM is 20.



**MORLEY**  **IAS**

**FIRE SYSTEMS**

by Honeywell

## Features

- Connection of a zone of non-addressable detectors to an analogue addressable fire system
- Built in isolation allowing system installation in stages without loss of protection
- Monitors open circuit and short circuit faults
- TRI-Colour Status LED
- Zone powered from addressable loop wiring or external 24V PSU
- Remote reset of non-addressable zone
- Compatible with:
  - Most non-addressable detectors
  - IS non-addressable detectors
- Monitoring of external power supply
- External fault input
- CPD approval to EN54-17 and EN54-18, LPCB and VdS
- DIN rail mountable, consistent with all other modules
- Support for an extended power supply range as low as 18Vdc 60mA with an External PSU

## Installation

The MI-DCZRM addressable Zone Monitor module fits into M200E-SMB and M200E-DIN. Mounting hardware and installation instructions are provided with each module.

## Part Number

Part Number	Description
MI-DCZRM	Addressable Zone Module



For further details on these or any other Morley-IAS products please contact your local distributor, Morley-IAS Business Manager or via our contact details found below. Morley-IAS by Honeywell - Providing a control panel solution, for fire industry professionals, committed to supporting our device partners.



Every care has been taken in the preparation of this datasheet but no liability can be accepted for the use of the information therein. Design features may be changed or amended without prior notice. © Morley-IAS by Honeywell 2015.

## Mechanical Specification

Height:	23mm
Length:	93mm
Width:	83mm
Weight:	110g
Max Wire Gauge for Terminals:	2.5mm <sup>2</sup>

## Electrical Specification

Operating Voltage Range:	18 to 28.5Vdc
Max. Standby Current:	288µA maximum (conventional zone connected to external supply)
LED Current	Red: 2.2µA @ 24Vdc Green: 6.6µA @ 24Vdc Yellow: 8.8µA @ 24Vdc

End of Line Resistor Value: 3.9k

## Environmental Specification

Temperature Range:	-20°C to +60°C
Humidity:	5% to 95% relative humidity (non-condensing)



by Honeywell

Honeywell Fire Safety MEA  
Emaar Business Park, Building 2  
2nd Floor, Office No. 201 Sheikh Zayed Road  
P.O.Box 232362, Dubai, U.A.E  
T: +971 4 4505 800 F: +971 4 4505 900

REF: M102-MI-DCZRM(0211)